

1/2 Power Sockets with 1/2" square drive according to DIN 3121 G 12.5



6-point w magnet – normal

Model	Item No.	A/F mm	L mm	D1 mm	D2 mm	L2 mm	Pk
KM1/2-8	230110	8	38	15.0	25	3.0	5
KM1/2-9	230111	9	38	16.0	25	4.0	5
KM1/2-10	230112	10	38	17.5	25	4.0	5
KM1/2-11	230113	11	38	18.5	25	5.0	5
KM1/2-12	230114	12	38	20.0	25	5.0	5
KM1/2-13	230115	13	38	21.0	25	6.0	5
KM1/2-14	230116	14	38	22.5	25	6.0	5
KM1/2-15	230117	15	38	23.7	30	6.0	5
KM1/2-16	230118	16	38	25.0	30	6.0	5
KM1/2-17	230119	17	38	26.5	30	6.0	5
KM1/2-18	230120	18	38	27.5	30	7.0	5
KM1/2-19	230121	19	38	29.0	30	7.0	5
KM1/2-20	230122	20	38	30.0	30	7.0	5
KM1/2-21	230123	21	38	31.0	30	8.0	5
KM1/2-22	230124	22	38	32.5	30	8.0	5
KM1/2-24	230125	24	45	35.0	30	10.0	5

Torx® E with magnet – normal

Model	Item No.	A/F #	L mm	D1 mm	D2 mm	L2 mm	Pk
KM1/2-E10	231510	E10	38	14.5	25	5.0	5
KM1/2-E11	231515	E11	38	15.0	25	5.0	5
KM1/2-E12	231511	E12	38	16.0	25	6.0	5
KM1/2-E14	231512	E14	38	18.0	25	8.0	5
KM1/2-E16	231513	E16	38	20.0	25	9.0	5
KM1/2-E18	231514	E18	38	22.0	25	9.0	5
KM1/2-E20	231516	E20	38	25.0	30	10.0	5
KM1/2-E22	231517	E22	45	27.0	30	10.0	5
KM1/2-E24	231518	E24	45	29.0	30	11.0	5



6-poin w magnet – inch

Model	Item No.	A/F Zoll	L mm	D1 mm	D2 mm	L2 mm	Pk
KM1/2-3/8	230150	3/8	38	–	–	–	5
KM1/2-1/2	230151	1/2	38	–	–	–	5

6-point w magnet – deep

Model	Item No.	A/F mm	L mm	D1 mm	D2 mm	L2 mm	Pk
KM1/2-8-L	230310	8	78	15.0	25	3.0	5
KM1/2-9-L	230311	9	78	16.0	25	4.0	5
KM1/2-10-L	230312	10	78	17.5	25	4.0	5
KM1/2-11-L	230313	11	78	18.5	25	5.0	5
KM1/2-12-L	230314	12	78	20.0	25	5.0	5
KM1/2-13-L	230315	13	78	21.0	25	5.0	5
KM1/2-14-L	230316	14	78	22.5	25	6.0	5
KM1/2-15-L	230317	15	78	23.7	30	6.0	5
KM1/2-16-L	230318	16	78	25.0	30	6.0	5
KM1/2-17-L	230319	17	78	26.5	30	6.0	5
KM1/2-18-L	230320	18	78	27.5	30	7.0	5
KM1/2-19-L	230321	19	78	29.0	30	7.0	5
KM1/2-20-L	230322	20	78	30.0	30	7.0	5
KM1/2-21-L	230323	21	78	31.0	30	8.0	5
KM1/2-22-L	230324	22	78	32.5	30	8.0	5
KM1/2-23-L	230325	24	78	35.0	30	10.0	5

